

97635 - F42TBX/835/A/ECO

GE Ecolux® Biax® T4 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse









CAUTIONS & WARNINGS

Caution

- · Lamp may shatter and cause injury if broken
- Remove and install by grasping only plastic portion of the lamp.

GENERAL CHARACTERISTICS

Lamp Type Compact Fluorescent - Plug-

Bulb T4 Base GX24-q4 **Equivalent Wattage** 190.0 W Rated Life 17000.0 hrs Starting Temperature (MIN) -18.0 °C Cathode Resistance 2.7 Ohm

66 picograms Hg per mean LEED-EB MR Credit

lumen hour

Rated Life (rapid start) @ Time 17000.0 @ 3.0/20000.0 @

12.0 h

Additional Info Dimmable with appropriate

dimming ballast./End of Life Protection (EOL)/TCLP

compliant

20.0 Hz

Primary Application Facilities;Retail

Display; Hospitality; Office; Restaurant; W

PHOTOMETRIC CHARACTERISTICS

Initial Lumens 3200.0 Mean Lumens 2690.0 Nominal Initial Lumens per Watt 76 Color Temperature 3500.0 K Color Rendering Index (CRI) 82.0

ELECTRICAL CHARACTERISTICS

Wattage 42.0 Voltage 135.0 Current (max) 5.25 A Open Circuit Voltage (after 265.0 V preheating) (MAX) Open Circuit Voltage (MIN) 515.0 V Lamp Current 0.32 A Preheat Voltage (MIN) 4.25 V Current Crest Factor (MAX) 1.7

DIMENSIONS

Supply Current Frequency

Maximum Overall Length 6.4000 in(162.6 mm)

(MOL)

Nominal Length 6.400 in(162.6 mm) Base Face to Top of Lamp 5.770 in(146.6 mm)

PRODUCT INFORMATION

Product Code 97635

Description F42TBX/835/A/ECO 60901-IEC-7442-2 **ANSI Code** Case

Standard Package

Standard Package GTIN 10043168976357

Standard Package Quantity 10 Sales Unit Unit No Of Items Per Sales Unit No Of Items Per Standard 10

Package

UPC 043168976350

NOTES

- 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).
- · Amalgam product experience stable brightness over a wider temperature range and in various operating positions.
- Based on 60Hz reference circuit
- Fluorescent lamp lumens decline during life