

5401A SERIES

INCREASED AMPERAGE & VOLTAGE SWITCHING

40 AMP CONTACTORS

APPLICATIONS

- Lighting loads
- Exhaust fans
- Electric and hot water heaters
- Refrigeration and defrosting



5401A

5441A

| CAT. NO. | UPC CODE | COIL VOLTS | NO. OF CONTACTORS | OUTPUT CONTACTS |
|----------|----------|------------|-------------------|-----------------|
| 5401A | 81019 | 120 | 1 | 3PST |
| 5441A | 81020 | 120 | 4 | 3PST |

FEATURES

CONTACT RATINGS: Can switch up to 40 AMPS per pole from 120VAC to 277V lighting loads, one to three circuits simultaneously.

EASY WIRING: Includes 120 volt control wiring compartment. 5441 has terminal strip pre-mounted for quick connection.

ENCLOSURE: Metal NEMA 1 Indoor enclosure (see pages 589-593 for enclosure dimensions).

| TYPE | VOLTAGE (VAC) | FLA | RATING |
|----------------------|---------------|----------|--------------|
| Tungsten* | 120 | - | 30A |
| Ballast* | 120/277 | - | 40A |
| LED* | 120/277 | - | 40A |
| Motor (Single Phase) | 120 240 | 40 40 | 3HP 7.5HP |
| Motor (3 Phase) | 240 480 | 40 40 | 10HP 20HP |

Coil Data: 120VAC @ 60Hz
6VA Holding/seal; 60VA inrush

* Ratings for single phase load

