

OSP/OSA Power Pack Series Provides low voltage power and line voltage control for Leviton Occupancy Sensors



Containing both a 24VDC supply and a 20A line voltage relay for most models of occupancy sensors, the Leviton Compact Power Pack provides low voltage power and line voltage control for Leviton occupancy sensors. Versions include Auto-ON and Manual-ON inputs for occupancy sensors, Hold-ON and Hold-OFF capabilities and a local input for momentary or maintained dry contact switches.


The internal relay can control up to 20A for 120, 230, 277VAC or 347VAC ballast loads and 120VAC incandescent loads. The OSP Power Pack Series is also used to supply power to the OSA Add-A-Relay model. The power pack conveniently mounts in a knockout hole of a standard junction box. The unit can be placed inside or outside the junction box with a simple twist-on nut.

APPLICATIONS

Use a Leviton Power Pack with Leviton occupancy sensors in the following applications:

- Anywhere optimal lighting and energy savings are desired
- Load shed/interface hold-OFF applications
- Retail hold-ON/bypass applications
- OSP20 Applications
 - Multi-circuit switching
 - Ceiling access lighting and energy management controls

- OSP20-RD Applications
 - Interface to Building Automation/ Management Systems (BAS/BMS) and HVAC
- OSP20-RDH Applications
 - Bi-level or A/B lighting
 - Shared emergency lighting
 - Inexpensive 3-way switching
- OSA20 Applications
 - Expanding circuit switching capacity
 - Cost-conscious mixed voltage solutions



PRODUCT DATA

FEATURES OSP20-ND0

- Self-contained transformer and relay
- Internal voltage regulator regulated 24VDC current, 150mA output
- Fast installation mounts inside or outside of a junction box, or inside a fluorescent ballast cavity with a simple twist-on nut
- Single or multiple luminaire control
- Zero-crossing circuitry
- UL 2043 Plenum Rated
- Companion Add-A-Relay provides additional capacity (OSA20-R00)
- NAFTA compliant

OSP20-RD0/OSP15-R30

Includes the same features as the OSP20-ND0, plus:

- Dry contact relay for combined sensor control of lighting and heating/air conditioning
- Dry contact for designing controlled closure
- Form A relay for interface to BAS/BMS


OSP20-RDH

Includes the same features as the OSP20-RD0, plus:


- Auto-ON and manual-ON inputs for occupancy sensors
- Hold-ON input when activated, unit is always ON regardless of any other input
- Hold-OFF input when activated, unit is always
 OFF regardless of any other input
- Local inputs for momentary or maintained dry contact low voltage switching
- Robust mechanical batching relay designed to perform as a Form C normally closed device
- Increased power supply output to 255mA
- Upon loss of power, latching relay maintains current state (closed or open)
- H.I.S. > (High In-rush Stability)
- Heavy-duty zero-crossing circuitry
- Robust mechanical latching relay

OSA20-R00

- •15A relay can be added to any OSP20 power pack for flexible design
- Provides cost-conscious design flexibility
- Inexpensive solution for mixed voltage lighting design
- Used for expanding circuit switching capacity
- Use OSP20 power packs for emergency lighting circuits and OSA20 Add-A-Relays for inexpensive control of normal lighting




WIRING DIAGRAM





OSP20 RDH BI-LEVEL SWITCHING



WIRING DESIGNATIONS

SIGNAL TYPE	COLOR	GAUGE
LINE VOLTAGE WIRES		
Line 120-230-277VAC (OSP20-Rx0)	Black	18AWG
Neutral	White	18AWG
Load	Blue	14AWG
Load	Blue	14AWG
CLASS 2 WIRES		
Power (24VDC)	Red	22AWG
DC Return	Black	22AWG
Occupancy Auto-ON	Blue	22AWG
Occupancy Manual-ON	Blue/White	22AWG
Hold-ON	Yellow	22AWG
Hold-OFF	Orange	22AWG
Local Switch Input	Yellow/Orange	22AWG

SIGNAL TYPE	COLOR	GAUGE	
HVAC WIRES			
Dry Contact Common	Green	22AWG	
Dry Contact NO (Normally Open)	Brown/White	22AWG	
Dry Contact NC (Normally Closed)	Brown	22AWG	

- All wires rated at 221°F (105°C), 600V insulation
- Class 2 wires are Teflon jacketed, for plenum applications
- ullet Dry contact wiring is Class 1 and Class 2 rated

POWER PACK CAPACITY FORMULA

Leviton power packs can be used to provide power to one or more occupancy sensors. Since current consumptions of occupancy sensors may vary, the best way to ensure you order the correct number of power packs and add-a-relays is by using this formula:

# of sensor Model As	
X .	
Sensor A current consumption rating	

of sensor Model Bs X Sensor B current consumption rating

of Add a Relays X 50mA

<150mA per power pack

DESCRIPTION	CURRENT CONSUMPTION
OSC04-I, OSC15-I, OSWHB-I, OSWLR-I, OSWWV-I	10-15 mA
OSC05-M, OSC05-U, OSW12-M	25 mA
OSC10-M, OSC10-U	35 mA
OSC20-M, OSC20-U	30 mA
OSA20-R Add-a-Relay	50 mA
ODCOP-SOW Switching Photocell	10 mA

Leviton Mfg. Co., Inc. Lighting & Energy Solutions



SPECIFICATIONS

ELECTRICAL			
Line Voltage	120-230-277 VAC		
Relay Rating	HVAC Relay: 0.5A @ 120VAC, 1.0A @ 30VDC		
ENVIRONMENTAL			
Operating Temperature Range	32-104°F (0-40°C)		
Relative Humidity	0-90% non-condensing, for indoor use only		
OTHER			
Construction	Case: High impact, UL rated plastic Relay: Class B (130°C) insulating material; silver alloy contacts Wire: 6" leads, 18AWG input; LV connections: 7" leads 22AWG		
Dimensions	2.400"H x 3.811"W x 1.432"D (60.96mm x 96.80mm x 36.37mm)		
Listings	UL/CUL Listed, FCC Certified, NOM Certified, and meets ASHRAE Standard 90. 2010 requirements		
Color	Black		
Warranty	Limited five-year warranty		

ORDERING INFORMATION

DESCRIPTION	CAT. NO.	POWER INPUT	RELAY RATING	CONTROL INPUT	POWER SUPPLY OUTPUT
Power Pack	OSP20-ND0	120-230-277VAC, 50/60 Hz	20A fluorescent/incandescent @ 120V, 20A fluorescent @ 230-277V; 1HP @ 120V, 2HP @ 240V	5mA, 24VDC	150mA, 24VDC
Power Pack with Dry Contact Relay	OSP20-RD0	120-230-277VAC, 50/60 Hz	20A fluorescent/incandescent @ 120V, 20A fluorescent @ 277V; 1HP @ 120V, 2HP @ 240V; HVAC: 0.5A @ 120VAC, 1A @ 30VDC	5mA, 24VDC	150mA, 24VDC
Power Pack with Dry Contact Relay	OSP15-R30	347VAC, 60 Hz	15A fluorescent @ 347V; 1HP @ 120V, 2HP @ 240V; HVAC: 0.5A @ 120VAC, 1A @ 30VDC	5mA, 24VDC	120mA, 24VDC
Add-A-Relay Unit with Dry Contact Relay	OSA20-R00	_	15A incandescent @ 120V, 20A fluorescent @ 120V, 20A fluorescent @ 277V, 15A fluorescent @ 347V; HVAC: 0.5A @ 120VAC, 1A @ 30VDC	5mA, 24VDC	_
Power Pack with Dry Contact Relay and Override Inputs for Occupancy Sensors	OSP20-RDH	120-230-277VAC, 50/60 Hz	20A fluorescent/incandescent @ 120V; 20A fluorescent@ 277V; 1HP @ 120V, 2HP @ 240V; HVAC; .05A @ 120VAC, 1A @ 20VDC and 15A fluorescent @ 347V; 1HP @ 120V; 2HP @ 240; HVAC: 0.5A @ 120V, 1A @ 30VDC	5mA, 24VDC	225mA, 24VDC

^{*} Consult factory for 208, 220, and 240V models

Leviton Manufacturing Co., Inc. Global Headquarters 201 N. Service Rd. Melville, NY 11747-3138 Tech Line: 1-800-824-3005 Fax: 1-800-832-9538

Leviton Manufacturing Co., Inc. Lighting & Energy Solutions 20497 SW Teton Avenue, Tualatin, OR 97062 • Telephone: 1-800-736-6682 • Fax: 503-404-5594 Tech Line (6:00AM-4:00PM P.S.T. Monday-Friday): 1-800-959-6004

Leviton Manufacturing of Canada, Ltd.

165 Hymus Boulevard, Pointe Claire, Quebec H9R 1E9 • Telephone: 1-800-469-7890 • FAX: 1-800-563-1853

Leviton S. de R.L. de C.V.

Lago Tana 43, Mexico DF, Mexico CP 11290 • Tel. (+52) 55-5082-1040 • FAX: (+52) 5386-1797 • www.leviton.com.mx

Visit our Website at: www.leviton.com/les