GT500W

RAB Controls



Gotcha Sensor with 110° view, surge protection, 500 Watt switching capacity, auto test logic and manual override.

Color: White

Weight: 0.7 lbs

Technical Specifications

Listings

UL Listing:

Suitable for wet locations

Electrical

Voltage:

Dimensions

120 or 277 volts AC 60 Hz

Power Consumption:

1W

Surge Protection:

Withstands up to 6000 volts

Wall Switch Manual Override:

Two flip logic prevents activation by momentary power outages. Override resets to auto after 6 hours or at dawn. No extra wiring needed.

Switching Capacity:

500 watts Incandescent @120 volts, 5 amps 250 watts Fluorescent

Sensor Characteristics

Time Adjustment:

10 seconds to 5 minutes

Photoelectric Control:

Deactivates lights during daylight. Fully adjustable for 24 hour operation or custom applications.

Detector Sensitivity:

Adjustable from 100% to 50%

Sensor Housing:

Made of tough, corrosion resistant polycarbonate

Project:	Туре:
Prepared By:	Date:

Features

500 Watt switching capacity

Detection:

Construction

Floodlights:

Made of tough, corrosion-resistant polycarbonate. For

extra or replacement floodlights, order cat# TUFFY in your choice of color. Accepts PAR-38 lamps, medium

RAB values USA manufacturing! Upon request, RAB

compliant with the Buy American Act (BAA). Please contact customer service to request a quote for the

may be able to manufacture this product to be

base, 150 watts max. Lamps not included.

Buy American Act Compliance:

product to be made BAA compliant.

110° view

Other

Warranty:

5 year sensor warranty

- New vandal resistant grill
- 6000 volt surge protection
- Temperature compensation
- Protected manual override with auto reset
- Double look down lens
- 5-Year, No-Compromise Warranty

3" 7.6 cm 2 1/4" 5.7 cm 4" 10.1 cm

Need help? Tech help line: (888) RAB-1000 Email: sales@rablighting.com Website: www.rablighting.com

Copyright © 2018 RAB Lighting Inc. All Rights Reserved Note: Specifications are subject to change at any time without notice