


Flat Terminal Connection – FLG400 (569170)



- Connects ERIFLEX FLEXIBAR or IBSB/IBSBR Power Braid to UD-250A/400A Single Pole Distribution Block
- Provides direct link between blocks and switch or circuit breakers



| | |
|-----------------------------|--|
| Part Number | FLG400 |
| Article Number | 569170 |
| Hole Size (HS) | 0.42" |
| A | 1.18" |
| B | 1.57" |
| Unit Weight | 0.22 lb |
| Certifications | EAC 0234267 (Russian Federation) RoHS |
| Standard Packaging Quantity | 10 pc |
| UPC | 78285659427 |
| EAN-13 | 8711893042726 |

| Design Guideline for Distribution Blocks, Power Blocks and Power Terminals | | | | | | | | | | |
|--|-----|-----|------|------|------|------|------|------|------|------|
| Derating according to Ambient* Temperature (°F) to maintain working temperature of 185°F | | | | | | | | | | |
| Ambient Temperature (°F) | 86° | 95° | 104° | 113° | 122° | 131° | 140° | 149° | 158° | 167° |
| Derating Coefficient (d) | 1 | 1 | 1 | 0.94 | 0.88 | 0.82 | 0.75 | 0.67 | 0.58 | 0.47 |
| *environment around the terminal blocks inside the enclosure | | | | | | | | | | |

WARNING

Pentair products shall be installed and used only as indicated in Pentair's product instruction sheets and training materials. Instruction sheets are available at erico.pentair.com and from your Pentair customer service representative. Improper installation, misuse, misapplication or other failure to completely follow Pentair's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

© 2017 Pentair All rights reserved

Pentair, CADDY, CADWELD, CRITEC, ERICO, ERIFLEX, ERITECH and LENTON are owned by Pentair or its global affiliates.

All other trademarks are the property of their respective owners. Pentair reserves the right to change specifications without prior notice.